

REDLINE Electronic Poker



Integrated converter: This eliminates the need for a standalone converter, which saves space and reduces costs.

Greater versatility: The integrated converter allows our vibrators to be used in a wider range of applications.

Significant improvement over conventional vibrators: Our vibrators produce a more uniform vibration, which results in better compaction.

Ideal for a variety of industries: Our vibrators are ideal for a variety of industries, including construction, manufacturing, and food processing.

Technical Data

| Model | Head Diameter r(mm) | Vibration (vpm) | Length of Protective Hose (m) | Length of Power Cable (m) | Thermal Needle Protection | Nominal Intensity (A) | Supply Voltage (1~) | Exit Voltage (3~) |
|----------|---------------------|-----------------|-------------------------------|---------------------------|---------------------------|-----------------------|---------------------|-------------------|
| RP40E/5 | 38 | 13,500 | 5 | 15 | Yes | 2.5 | 230V 50/60 Hz | 230V 200 Hz |
| RP50E/5 | 50 | 12,000 | 5 | 15 | Yes | 4 | | |
| RP60E/5 | 60 | 12,000 | 5 | 15 | Yes | 6 | | |
| RP70E/5 | 70 | 12,000 | 5 | 15 | Yes | 8 | | |
| RP40E/7 | 38 | 13,500 | 7 | 15 | Yes | 2.5 | | |
| RP50E/7 | 50 | 12,000 | 7 | 15 | Yes | 4 | | |
| RP60E/7 | 60 | 12,000 | 7 | 15 | Yes | 6 | | |
| RP70E/7 | 70 | 12,000 | 7 | 15 | Yes | 8 | | |
| RP40E/12 | 38 | 13,500 | 12 | 15 | Yes | 2.5 | | |
| RP50E/12 | 50 | 12,000 | 12 | 15 | Yes | 4 | | |
| RP60E/12 | 60 | 12,000 | 12 | 15 | Yes | 6 | | |
| RP70E/12 | 70 | 12,000 | 12 | 15 | Yes | 8 | | |

